

Band Pass Filter 1298~1702MHz



Electrical & Mechanical Specifications	
Center Frequency	1500MHz
Frequency Range	1298~1702MHz
Insertion Loss in BW	1.0 max.
Passband Ripple	1.0 max.
Return Loss in BW	17min. (19.5)
Rejection	70 min. @ 1200MHz 70 min. @ 1800MHz 55 min. @ 1800~5100MHz
Input Power	150W max.
IN/OUT Impedance	50
Operating Temp. Range	-20 ~ +85
Connector	IN: N(Female)/ OUT: N(Male)
Finish	Black Epoxy Painting

